

Objectives


- Experience with "Transmit CAN" and "Receive CAN" components
- Experience masking data to get the message you want
- Demo of how to use H1/S90 compliance block when using IO Modules



Masking CAN messages

Masking: What are we looking for?

- Our illustrative example will be getting the actual PWM duty cycle of the output on an IO Module.
- This is needed as an input by some PLUS+1 Compliance Blocks, but not currently transmitted by the IO Module
- Question: Where would we find the message format that has to be sent to the IO Module to request this information????
- Answer: In the PLUS+1 IO Modules
 Communication document



Masking: What are we looking for?

- Need to send a message to:
 - Tell the IO Module to start sending information and with what frequency:
 - SubCmd 12 Configure Timing
 - SubIdentifier 96 Multifunction Out Status
 - Note: Pin affected by the command is designated by "channel"
 - First pin of certain type designated channel 0, second is channel 1, and so on



Masking: Getting the details

Initiator message we send once:

Configure Timing (SUBCMD 12)

	SUBCMD CAN B 1		Data 1 CAN B 3			Data 4 CAN B 6	Timeout
0xFF	0x0C	Sub-identifier*	Channel [†]	Time [‡] (LSB)	Time [‡] (MSB)		 None

[†]If the message being enabled or disabled has a "channel" value associated with it, please enter the value here.

Status message we receive back regularly

Multifunction Out Status (SUBCMD 96)

	Data 0 CAN B 1	Data 1 CAN B 2				Data 5 CAN B 6	
0x60	Channel*	Value [†] (LSB)	Value [†] (MSB)	ActPWM [‡] (LSB)	ActPWM [‡] (MSB)	Status [§]	

^{*}Indicates the channel.

Identifier Table

N1	TxID	Rx ID
0	0x180	0x300
1	0x188	0x308
2	0x190	0x310
3	0x198	0x318
4	0x1A0	0x320
5	0x1A8	0x328
6	0x1B0	0x330
7	0x1B8	0x338
8	0x1C0	0x340
9	0x1C8	0x348
10	0x1D0	0x350
11	0x1D8	0x358
12	0x1E0	0x360
13	0x1E8	0x368
14	0x1F0	0x370
15	0x1F8	0x378

^{*}Identifies the communication message gets a new timing value.


[‡]New timing value, which can be the new cycle or the new timeout value, depending on the message.

[†]Actual measured feedback value in 0.1 mA.

[‡]PWM duty cycle.


[§]Status of the output.


Application





Status passed to block, as though it were a non-IO pin













Hands-On Exercise

Exercise

- Open Project IO_Module_PWM in Advanced CAN folder
- Use S90 EDC Compliance Block to drive outputs using IO Module
 - Add another S90 Compliance Block for IO Module output pins C1p11
 & C1p12
 - Use IO_ActPWM SCS file in Advanced CAN folder with code from preceding slides to get Pin Status Feedback from IO Module pins needed by S90 Compliance Block

- Error 15
 - Net Type Redefined, Signal

```
View Logical Net

*** ERROR 15 *** [CHPARGU1] NET TYPE REDEFINED, SIGNAL: {AN212} TYPE1: {S32} TYPE2: {CS32}

Component Position: module=SC24 10 PRIMARYT page=!TOP!Application!Valves!S90 EDC 2 x=3550000 y=400000

View Logical Net

Compiler Messages Build Messages Error/Warning/Hint Messages
```

- Error 24
 - Outputs Connected On Component

```
*** ERROR 24 *** [CHPARGU1] OUTPUTS CONNECTED ON COMPONENT: {3 Character}, ENTRY X{1}


Component Position: module=SC24 10 PRIMARYT page=!TOP!Application!Valves!S90 EDC 2 x=3200000 y=550000

View Logical Net

*** ERROR 24 *** [CHPARGU1] OUTPUTS CONNECTED ON COMPONENT: {3 Character}, ENTRY X{1}

Compiler Messages | Build Messages | Error/Warning/Hint Messages |
```

- Outputs Connected on Component
 - Missing redundant word: MULTIPLE



```
*** ERROR 24 *** [CHPARGU1] OUTPUTS CONNECTED ON COMPONENT: {3 Character}, ENTRY X{1}
Component Position: module=SC24 10 PRIMARYT page=!TOP!Application!Valves x=3025000 y=2400000
View Logical Net


*** ERROR 24 *** [CHPARGU1] OUTPUTS CONNECTED ON COMPONENT: {3 Character}, ENTRY X{1}
Component Position: module=SC24 10 PRIMARYT page=!TOP!Application!Valves x=3025000 y=2350000
View Logical Net
```

Two signals of type 3-Character-Constant input to Entry X1

- Frror 21
 - No Output Connected On Component

```
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {AND2}, ENTRY A{1}
Component Position: module=SC24_10_PRIMARYT_page=!TOP!Application!Valves!S90_EDC_2!S90_EDC!Ctrl_A!Cal_Params x=1425000_y=2025000_
View Logical Net
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {AND2}, ENTRY A{1}
Component Position: module=SC24 10 PRIMARYT page=!TOP!Application!Valves!S90 EDC 2!S90 EDC!Ctrl A!Cal Params x=1450000 y=1825000
View Logical Net
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {Positive Transition}, ENTRY A{1}
Component Position: module=SC24_10 PRIMARYT page=!TOP!Application!Valves!S90_EDC_2!S90_EDC!Ctrl_A!Fault_Detect x=625000 y=2350000
View Logical Net
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {AND4}, ENTRY A{3}
Component Position: module=SC24_10 PRIMARYT page=!TOP!Application!Valves!S90 EDC 2!S90 EDC!Ctrl A x=3000000 v=1475000
View Logical Net
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {AND2}, ENTRY A{1}
Component Position: module=SC24_10_PRIMARYT_page=!TOP!Application!Valves!S90_EDC_2!S90_EDC!Ctrl_B!Cal_Params x=1425000_y=2025000
View Logical Net
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {AND2}, ENTRY A{1}
Component Position: module=SC24 10 PRIMARYT page=!TOP!Application!Valves!S90 EDC 2!S90 EDC!Ctrl B!Cal Params x=1450000 y=1825000
View Logical Net
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {Positive Transition}, ENTRY A{1}
Component Position: module=SC24_10 PRIMARYT page=!TOP!Application!Valves!S90_EDC_2!S90_EDC!Ctrl_B!Fault_Detect_x=625000_y=2350000
View Logical Net
*** ERROR 21 *** [CHPARGU2] NO OUTPUT CONNECTED TO COMPONENT: {AND4}, ENTRY A{3}
Component Position: module=SC24 10 PRIMARYT page=!TOP!Application!Valves!S90 EDC 2!S90 EDC!Ctrl B x=3000000 y=1475000
View Logical Net
INFORMATION: {8} ERRORS AND {0} WARNINGS FOUND BY {chpargu2}
```

 View Logical Net – Sometimes not helpful if error is in disabled page, but ...



- Error 66
 - Multi-Defined Alias

```
*** ERROR 66 *** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_Thld}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 *** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_EndCrnt}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 *** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 *** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 *** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 *** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 *** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {S90_EDC_L_A_EE_CalFlg}, FILE1: {SC24_10_PRIMARYT.exr}, SIGNAL1: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {_NVINT[NVBase_MAINTASK+ *** ERROR 66 **** [GLINK] MULTI DEFINED ALIAS: {_N
```

What causes it?

